









Ceiling mount bracket and junction box for fixed lens vandal dome cameras

DWC-MV9CMJ



WHAT'S IN THE BOX

Ceiling Mount Bracket Mounting Screws and Anchors (PA4x25mm, head diameter 6.6mm)		x3
Bracket-to-Junction Box Mounting Screws (PM4x12mm, head diameter 8mm)		x4
Neck Connection Screws (PWM3x6mm)		x2
Waterproof Rings for Mounting Screws		x8
Ceiling Mount Bracket Mounting Template		x1
Junction Box Mounting Screws and Anchors (PA4x25mm, head diameter 8mm, not used)		x4
Camera Mounting screws (PM4x16mm, head diameter 8mm)		x4
Cable Gland Connector		x1

NOTE: Download all your support materials and tools in one place.

1. Go to: <http://www.digital-watchdog.com/resources>
2. Search your product by entering the part number in the **'Search by Product'** search bar. Results for applicable part numbers will populate automatically based on the part number you enter.
3. Click **'Search'**. All supported materials, including manuals and quick start guide (QSGs) will appear in the results.



INSTALLATION

- 1 Assemble the ceiling mount bracket by connecting the bracket base, arm and connector using the neck connection screws.
- 2 Using the mounting template or the mounting bracket itself, mark and drill the necessary holes on the mounting surface.
- 3 Secure the mounting bracket to the mounting surface using the screws and anchors that were included with the mount.
- 4 Mount the junction box base to the ceiling bracket using the bracket-to-junction box mounting screws and waterproof rings.
- 5 To mount the camera to the junction box, remove the dome from the camera base using the wrench included with the camera.

NOTE: Do not touch the lens when handling the camera.

- 6 Pass wires through and make all necessary connections. Arrange the cables in the junction box base. Use the waterproof cap and gasket with the network cable to reduce the risk of water leaks. See the camera's QSG for more information.
- 7 Secure the camera to the mounting bracket using the included camera mounting screws.
- 8 Adjust the camera's lens position and angle and place the cover dome on the camera base to complete the installation.

